

Creon Analog Smart Zigbee Led Controller 0-10V/ 1-10V Light Dimming Controller. Smart Home Dimmer Work With Alexa.It needs to be used in conjunction with the 0-10V dimmable driver. Compatible with 0-10V/1-10V drive power. The lights can be dimmed and controlled, and it supports mobile APP control. Need to use a gateway to connect to the APP.

Key Points

- App Control For IOS and Android.
- Compact enough to be installed in box or ceiling.
- Custom open/close time brightness level.
- Color and scene according to your personal requirements.
- Can be linked with other smart , such as music player, diffuser, bedroom lamp, etc.
- Remote access.
- These devices works with many ZigBee Light Link Gateways voice control.
- Schedule and Triggering.

Specifications

- Input power: AC100-240V AC.
- Output voltage: 0/1-10V.
- Current: 20mA.
- Wireless frequency: zigbee 3.0.
- Transmission distance: 30 meters.
- IP rating IP20.
- Pairing Button.
- Required to work with ZigBee 3.0 gateway.
- Size(LxWxH)62x39mmx25mm.
- White Finish.
- 0/1-10V zigbee dimmers are suitable for 0-10V dimmable drivers.
- Material: plastic.
- Working Temperature -20°C to 40°C.

Installations

Ceiling Gidden or wall box hidden mounting.

Warranty

One year limited warranty against defects in manufacturing.

Ordering Code

CR10T-ADIM-ANALOG-W-1CH

W-White

Product Image



Product Dimensions

